
Some signal to noise calculations

- Signal:
- $S_{21min} = 0.01$
- P_{in} (the maximum power Nino claims to put in his MKIDs) = 10 pW (i.e. 10⁻⁸ dBm)
- $P_{out min} = S_{21min}^2 P_{in} = 0.001 pW = 1 fW (on resonance)$
- Supose the foton dynamic range maps into a 30 to 60 degree change of MKID's phase.
- That implies a Pout dynamic range between 0.5 and 0.866 P_{out min}.
- That is 0.35 P_{out min} = 0.35 fW.
- If we want an R of 100, we need to be able to discriminate $\Delta P_{out}(R=100) = 0.0035 P_{out min} = 0.0035 fW$.



Some signal to noise calculations

- HEMT Noise:
- The HEMT noise between 4 GHz and 8 GHz is ~ 5 K.
- $P_n = K_b T BW$ ($K_b = 1.38 \ 10^{-23}$ and BW is the bandwidth per MKID channel, say 2 MHz)
- $P_n = 1.38 \cdot 10^{-23} \cdot 5 \cdot 2 \cdot 10^6 = 0.138 \text{ fW}$
- If the noise is only white Gaussian, integrated over 100us is reduced by ~ 600 times.
- $P_{n_{\text{filtered}}} = 0.00023 \text{ fW}.$

Cryo4-12 SN421D Noise and Gain at 22.1K
Vd=1.2V 17.4mA; Vg1= -1.0V Vg2= -1.0V

June, 2011; Quad B RCM = 4625-20

25
0
0
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15

GHz

Signal to noise: $\Delta P_{out}(R=100) / P_{n \text{ filtered}} \sim 10$

